## 2015-2017 Ford F-150 Projector Headlights Switchback Splicing Instructions SKU 111357/ 111358

Modified on: Wed, Jun 21, 2023 at 1:20 PM

2015-2017 Ford F-150 Projector Headlights Switchback Splicing Instructions 2015-2017 Ford F150 Projector Headlights Switchback Splicing Instructions

SKU# 111357, SKU# 111358



5150 Eucalyptus Avenue Unit A Chino, Ca. 91710 888.360.3696



Read complete instructions before installation! Improper installation may void warranty

Description: Wire splice for 2015-2016 Ford F150 Switchback

For the installation please note that you will have two loose wires for the switchback function

Brown wire will be (+) Positive and the black wire will be (-) Negative.

Both wires will need to be spliced into the turn signal bulb for the switchback function to work properly.



The two wires located at the bottom of the new AnzoUSA headlight will operate the switchback function.



Pictured above is a comer light bulb harness with integrated turn signal and parking light function.



To check the polarity of the wires, you can use a light testing tool to check. First turn on the turn signal and ground your light testing tool and insert the tip of the tool into the socket. When the light testing tool flashes you have located the (+) positive turn signal wire.



Locate the black (-) negative wire from the AnzoUSA headlight and splice that wire into the (-) negative wire on the turn signal harness, typically this wire will be black.



Locate the brown (+) positive wire from the AnzoUSA headlight and splice that wire into the (+) positive turn signal bulb wire. The positive turn signal bulb wire is typically the outside wire opposite of the negative wire.



Once you are done with the installation check all functions to make sure they are working properly. If you need more assistance with the installation please see our Youtube channel or contact us at \$88-360-3696 Mon-Fri \$AM - 5PM PST.

https://www.youtube.com/watch?v=xXUFKhVfJQg

AnsoUSATM products are covered, by a limited one (1) year warranty, to be free of manufacturer's defects. However, certain AnsoUSATM product categories have warranty policies which differ from this standard, please contact your representative for detailed category information. Damage due to improper installation or road hazards is not covered. Seller and manufacturers' only obligations shall be to replace the product proven to be defective. Neither seller nor manufacturer shall be liable for any injury, loss or damage, direct or consequential, artising out of the use of or the inability to use the product. Before using, user shall determine the suitability of the product for its intended use, and user assumes all risk and liability whatsoever in connection therewith.

© 2008 AnnoUSATM. All rights reserved.